

### Description

The JSL-B35 is a high-performance 7-inch indoor video intercom terminal designed for modern residential and commercial buildings. It integrates video talk-back, remote unlocking, emergency call, and multiple alarm zone functions, providing users with convenient, safe, and intelligent home communication and security management. The unit supports wall-mounted installation and features a stylish ABS+PMMA housing with a slim profile for aesthetic integration into any interior.



### Main Features

- Supports video talk-back with outdoor stations
- Remote door unlocking capability
- Supports 8 to 4 alarm zones
- Emergency call to management center at any time
- Cancel garrison and arming with password/code
- Set garrison and arming via room station using code
- Receive and delete information from guard center
- Optional image capture and storage
- Information search function
- 7-inch touch digital screen with color display
- Adjustable image brightness, volume, and color
- Wall-mounted design (mounting plate: 60×60 mm)
- Preset SD interface for future storage expansion

### Specifications

<b>Display</b>	7-inch TFT LCD color screen (touch digital)	<b>Interface</b>	SD card slot (optional)
<b>Resolution</b>	CCIR 350 TV lines (horizontal)	<b>Material</b>	ABS + PMMA housing
<b>Scan Frequency</b>	CCIR H: 15,625 ± 400 Hz / V: 47 ± 3 Hz	<b>Power Supply</b>	DC 17V - 20V
<b>Video Standard</b>	CCIR	<b>Quiescent Current</b>	< 20 mA
<b>Installation</b>	Wall-mounted	<b>Emergency Call</b>	Direct call to management center
<b>Image Adjustment</b>	Brightness, color, and volume adjustable	<b>Work Temperature</b>	0°C - +45°C
<b>Video Functions</b>	Video talk-back, monitoring outdoor station	<b>Working Humidity</b>	45%-95%
<b>Unlocking</b>	Remote unlock via intercom system	<b>Dimensions</b>	224 mm (W) × 130 mm (L) × 23 mm (D)
<b>Alarm Zones</b>	8 to 4 zones configurable	<b>Color</b>	White
<b>Emergency Call</b>	Direct call to management center	<b>Weight</b>	0.65 kg