# Low power battery camera

## LS-BC4R-4G

## Key Features

- 1. 3MP 4G Mini battery camera
- 2. Built-in 4G module, different modules in different countries
- 3. built-in 2400mAh batteries
- 4. Two-way voice intercom
- 5. Cloud storage and TF card storage maximum 128G（without TF card）
- 6. 4G network remote viewing/playback via APP (UBox PRO)
- 7. Automatic video recording and message push when human body motion wakes up, radar detection distance: 5 meters
- 8. Alarm deployment time can be set
- 9. 3.2mm lens,built-in 940nm infrared light, IR distance 8 meters
- 10. Not waterproof, suitable for indoor use

## Specifications

| Model No. | LS-BC4R-4G | |
|---|---|---|
| General | Main processor | Ingenic-T31ZL |
| | APP Operation System | Android, IOS |
| | Image Senor | 1/2.9" Image Sensor |
| | Compression | H.264+/H.265 |
| | Resolution | 2304*1296 3MP |
| Internet Connection | 4G | TD-LTE,TD-LTE / LTE FDD TD-LTE / LTE-FDD |
| | 4G Version | CN/ AU/ EU/ JP/ US/ ASEAN (Optional) |
| Alarm | Detection Mode | Radar + motion detection |
| | Detection Distance | 5 meters |
| | Detect Angle | 95° |
| | Alarm Mode | Realtime calling or push message |
| Night Vision | Full color night vision | 0.001 Lux |
| | IR LED | 940 nm infrared LED, 8M IR distance |
| Audio | Built-in speaker | High sensitivity-38dB |
| | Built-in microphone | 0.25W |
| Lens | Lens | 3.2mm |
| | Lens Angle | 110° |
| Storage | Cloud Storage | storage when alarm recording |
| | Local Storage | TF Card Max 128G |
| Power | Power Supply Mode | DC5V+ Build in Batteries |
| | Battery Capacity | Build in 2400mAh battery |
| | Operating power consumption | 2W |
| | Standby consumption | 0.003W |
| Others | Working Environment | Indoor |

| | | |
|---|---|---|
| | Operation Temperature | -30°~+60° |
| | Humidity | 0%~90%RH |
| **Package** | N.W. | |
| | Giftbox size | |
| | Quantity in carton | |
| | G.W. | |
| | Carton size | |